

# D.A.V. electronics


Digital Audio Visual

[Home](#)
[Products](#)
[Servicing](#)
[Contacts](#)
[Enquiries](#)
[Sales](#)
[Links](#)

## THE BROADHURST GARDENS NO. 2 mk II 4 CHANNEL MICROPHONE PRE-AMPLIFIER



[Click here for enlarged image](#)



[Click here for enlarged image](#)

1U rackmount high quality 4 channel microphone amplifier.

### Features

The features of this microphone amplifier consist of low noise and low distortion. It offers switched gain controls for high accuracy level setting, level indication, switchable high pass filters, input pads.

### Specifications

<b>Frequency response:</b>	10Hz - 150KHz $\pm$ 0.25dB	<b>High pass filter:</b>	68Hz @ 12dB per octave
<b>Distortion:</b>	Less than 0.01% Typ, 0.001% 1KHz @ +20dBu o/p	<b>Phase reversal:</b>	All channels (Switchable)
<b>Noise:</b>	25 microvolts [-110dB ref +20 dBu. Bandwidth 10Hz- 18KHz input loaded 150 ohms, 32dB gain].	<b>Level Indication:</b>	Red LED +18dBu Green LED +8dBu Can be pre-set for your operating level
<b>48v phantom:</b>	All channels (Switchable)	<b>Clipping level:</b>	+29 dBu
<b>26dB pads:</b>	All channels (Switchable)	<b>Connectors:</b>	IEC mains, XLR's on rear
<b>Gain range:</b>	22dB - 66dB in 4dB steps. [pad in -4dB - +40dB]	<b>Dimensions:</b>	19" 1U rack mount. Depth = 150mm
		<b>Price:</b>	P.O.A.

If You wish to purchase this product please click on **Contacts** or **Sales** below.

If you wish to ask a question about this product please click on **Contacts** or **Enquiries** below.

[Top](#) | [Enquiries](#) | [Sales](#) | [Contacts](#)